

| MODE | ACTION | EXPERIENCE | POWER LEVEL | RESULT | AUTOMATIC FUNCTION |
|------|---|-------------------|-------------|---|--|
| 1 | Turn on wall switch | Standard lighting | 66% | Lighted mirror turns on at 66% light level for general room illumination. | Energy Save mode: If lights remains on for more than 60 minutes, lighting automatically reduces to 33% light level (mode 5). |
| 2 | First Touch  | Task lighting | 100% | Light level increases to 100%. | |
| 3 | Second touch  | Off | 0% | Lighted mirror turns off. Leaf remains lit. | If not touched for more than 60 minutes, the next touch turns light on at 66% light level. (mode 1) |
| 4 | Third Touch  | Night Glow | 1.5 to 0.1% | Lighted mirror turns on at 1.5% light level for nighttime safety. | Eye-Sensitivity Adjustment gradually reduces light level from 1.5% to 0.1% over 20 minutes as eyes adjust to low light. |
| 5 | Fourth Touch  | Soft lighting | 33% | Light level increases to 33%. | No automatic changes; lights are in Energy Save mode. |
| 6 | Fifth Touch  | Standard lighting | 66% | Light level increases to 66%; cycle starts again. | |

Notes:

- Check local electrical code to determine if wall switch is required near entryway to room.
- If wall switch controlling the lighted mirror is a motion sensing type, it will include a delay that automatically turns the circuit off after a preset amount of time. When power is returned, the lighted mirror will turn on at mode 1, 66% light level.
- Any time power is eliminated to the lighted mirror (switched, circuit breakers, power outage, etc.) the default light level when power is returned is the 66% light level,